

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11) Publication number:

0 405 952 A2

(12)

EUROPEAN PATENT APPLICATION

(21) Application number: 90307046.4

(51) Int. Cl.⁵: G11B 7/125, H01S 3/10

(22) Date of filing: 27.06.90

(30) Priority: 28.06.89 JP 165577/89

(43) Date of publication of application:
02.01.91 Bulletin 91/01(84) Designated Contracting States:
DE FR GB IT NL(71) Applicant: SHARP KABUSHIKI KAISHA
22-22 Nagaike-cho Abeno-ku
Osaka 545(JP)(72) Inventor: Numata, Tomiyuki, Akebono-Ryo
2613-1, Ichinomoto-cho
Tenri-shi, Nara-ken(JP)

Inventor: Kojima, Kunio

2-7-8-305 Shlbatsuji-cho

Nara-shi, Nara-ken(JP)

Inventor: Deguchi, Toshihisa

C-722 Daiya-Haitsu-Gakuenmae, 2-200-5
Gakuen

Daiwa-cho, Nara-shi, Nara-ken(JP)

Inventor: Terashima, Shigeo


95-86 Kaminosho-cho

Nikaido, Tenri-shi, Nara-ken(JP)

(74) Representative: Brown, Kenneth Richard et al
R.G.C. Jenkins & Co. 26 Caxton Street
London SW1H 0RJ(GB)

(54) Semiconductor laser driving circuit.

(57) The invention provides an improvement of the conventional laser driving circuit mainly including a control logic circuit, a reproducing power producing circuit, and a recording power producing circuit for preventing a recording film of a disk from being damaged by a laser in a reproducing mode. The improved respect is addition of a voltage monitoring circuit and a bypass transistor for an abnormal signal. The voltage monitoring circuit monitors a voltage drop caused in the control logic circuit and supplies a voltage abnormality indicating signal, thereby causing the bypass transistor to be conductive for allowing the abnormal signal to be flown therethrough.

Fig. 3

EP 0 405 952 A2

SEMICONDUCTOR LASER DRIVING CIRCUIT

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a semiconductor laser driving circuit which is used in an optical disk recording and reproducing system wherein information is recorded on and reproduced from an optical disk.

2. Description of the Related Art

In the conventional optical disk system for recording or reproducing information with a laser beam, in a recording mode, it serves to follow the steps of intensifying or mitigating a laser output pulsewise in accordance with information to be recorded, changing the power of a laser beam spot restricted on a disk by an optical system accordingly, and changing an optical or magnetic state of a beam-irradiated spot of a recording film formed on the disk for recording the information. In a reproducing mode, it serves to follow the steps of irradiating the disk with a laser beam having such an intensity as not transforming the recording film and detecting the reflected beam for reproducing the information recorded thereon.

It will be understood from this function that it is necessary to keep a laser output at a predetermined value in both the recording and the reproducing modes. Because the semiconductor laser is subject to the change of an ambient temperature of the used semiconductors, the laser output is required to be controlled so that it can avoid any influence affected by the temperature change or the other factors.

Fig.1 is a circuit diagram showing a conventional laser driving circuit, which mainly includes a control logic circuit 11, a reproduction power producing circuit 12, and a recording power producing circuit 13. Further, it is seen from this figure that a laser 3 and a photodetector 4 are also added to the circuit. The photodetector 4 may employ a photodiode. As shown, the control logic circuit 11 is connected to a +5V power source and the reproduction power producing circuit 12 and the recording power producing circuit 13 are connected to a +12V power source.

The reproduction power producing circuit 12 includes a transistor 2 for driving the laser 3 in a reproducing mode, a current-to-voltage converting circuit 5 for converting the current generated in the photodetector 4 into a voltage, an operational am-

plifier 6 for amplifying the converted voltage, and a switching circuit 1 for switching on and off a contact between the operational amplifier 6 and the transistor 2.

5 The recording power producing circuit 13 consists of a transistor 9 for driving the laser 3 in a recording mode, a recording power setting circuit 8 connected to the base of transistor 9, and a switching circuit 10 for switching on and off a contact between the transistor 9 and the laser 3.

10 In operation, in the reproducing mode, the control logic circuit 11 supplies the reproduction signal a to the switching circuit 1, thereby switching on the switching circuit 1 and activating the laser 3. Then, the laser 3 radiates a beam c to the photodetector 4, which generates a current d. Then, the current d is supplied to the current-to-voltage converting circuit 5 in which the current d is converted into a voltage e and is amplified by the operational amplifier 6. The amplified voltage is supplied to the transistor 2 through the switching circuit 1. The transistor 2 serves to adjustably produce the reproduction driving current I_R . In summary, this operation can be summarized as detecting the laser beam and applying negative feedback to the detected signal for keeping a driving current constant.

15 In the recording mode, on the other hand, the recording power setting circuit 8 supplies a predetermined signal to the transistor 9 in which the recording driving current is adjustably produced, while the control logic circuit 11 supplies the recording signal b to the switching circuit 10. The switching circuit 10 is switched on and off in accordance with the magnitude of the signal b. The on-and-off switching results in modulating a recording driving current I_W and superposing the recording signal on the driving current I_W . At this time, for interrupting the control operation, the reproduction driving current I_R is kept at the value given immediately before executing the operation in the recording mode by a sample holding circuit (not shown).

20 As mentioned above, the foregoing semiconductor laser driving circuit has two or more power voltages. That is, the control logic circuit 11 is connected to the +5 power source and the reproduction power producing circuit 12 and the recording power producing circuit 13 are connected to the +12 power source. In this case, the switching of the power sources may result in bringing about a time lag between the leading and the trailing edges of the former power source and those of the latter one.

Fig.2 is a graph showing the state of a voltage

caused when the time lag appears, in particular, when the power sources are interrupted in driving the laser. In the reproduction mode, assuming that the power sources are interrupted at a time t_0 , as shown in the curves A and B of the graph, the +5v power source connected to the control logic circuit 11 supplies the lowest possible operating voltage for activating the logic circuit 11 at a time t_1 and the +12v power source connected to the reproduction power producing circuits 12 and 13 also supplies the lowest possible operating voltage for activating the circuits 12 and 13 at a time t_2 . At an interval Δt between the times t_1 and t_2 , the control logic circuit 11 cannot keep its logic level stable, thereby switching on the switching circuit 10 as shown in the curve C and supplying the recording driving current I_w as shown in the curve D to the laser 3. It results in bringing about a drawback that the laser output reaches such a power that it can transform the recording film formed on the disk and thus gives damage to the information recorded on the disk.

SUMMARY OF THE INVENTION

It is therefore an object of the present invention to provide an improved semiconductor laser driving circuit which is capable of inhibiting abnormal rise of a laser power often caused when the power sources are interrupted in driving the laser and preventing the information recorded on the recording film of the disk from being damaged.

To overcome the drawback, in addition to the foregoing prior art, the invention further provides a means for monitoring the power sources of the semiconductor laser driving circuit, in particular, the power source of the control logic circuit and a means for reducing driving current supplied to the semiconductor laser immediately before or when the source voltage reaches the lowest possible operating value.

Further objects and advantages of the present invention will be apparent from the following description of the preferred embodiments of the invention as illustrated in the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig.1 is a circuit diagram showing a conventional semiconductor laser driving circuit;

Fig.2 is a graph showing the operation of the conventional semiconductor laser driving circuit;

Fig.3 is a circuit diagram showing an improved semiconductor laser driving circuit according to a first embodiment of the invention;

Fig.4 is a graph showing the operation of the improved semiconductor laser driving circuit; and Fig.5 is a circuit diagram showing an improved laser driving circuit according to a second embodiment of the invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Fig.3 is a circuit diagram showing a first embodiment of the present invention. The embodiment is an improved semiconductor laser driving circuit designed on the foregoing prior art. The same components of this embodiment as the prior art are referenced by the same reference notes. The improved, that is, different respect of this embodiment from the conventional circuit is that a voltage monitoring circuit 23 is provided in a part of the power source circuit of the control logic circuit 11 and a bypass transistor 21 is connected in parallel to the laser 3. The voltage monitoring circuit 23 comprises a Zener diode ZD, a comparator 22 and resistors R_1 , R_2 , R_3 connected to these former two components. The cathode of the Zener diode ZD is connected to the power source of the control logic circuit 11 and a non-inverting input terminal of the comparator 22 through the resistor R_3 . The resistors R_3 and R_2 connected in series serve as a voltage divider of the source voltage V_D so that they reduce the voltage V_D to a two-thirds value. Hence, the reduced voltage is applied to the non-inverting input terminal of the comparator 22. The other end of the resistor R_2 is connected to the ground. The anode of the Zener diode ZD is connected to both the inverting input terminal of the comparator 22 and the ground through the resistor R_1 . It results in making the voltage applied to the inverting input terminal smaller than the source voltage V_D by the Zener voltage of 1.5 V.

Fig.4 is a graph showing the relation among a drop of the source voltage V_D , a drop of the voltage applied at the inverting input terminal of the comparator, a drop of the voltage applied at the non-inverting input terminal thereof, a voltage abnormality indicating signal f , and an operating state of the transistor 21 when the power source is interrupted. Assuming that the power source is interrupted at a time t_0 , the voltages at the time point are such that the power source voltage V_D is equal to 5V, the inverting input terminal voltage is equal to $V_D - 1.5V = 3.5V$, and the non-inverting input terminal voltage is equal to $V_D \times 2/3 = 3.3V$. After the time t_0 , these voltages gradually drop. When the source voltage V_D reaches 4.5V at a time t_1 , the inverting input terminal voltage and the non-inverting input terminal voltage equally reach 3V. After the time t_1 , the relation between both voltages is reversed to be such that the non-inverting input terminal volt-

age is greater than the inverting input terminal voltage. This state change of the comparator 22 after the time t_1 brings the output of the comparator, that is, the voltage abnormality indicating signal f into a high-level one. This high-level signal results in causing the conduction of the transistor 21 and short-circuiting the laser 3. Hence, assuming that the lowest possible operating voltage of the control logic circuit 11 is 4.4V, for example, when the source voltage V_D reaches 4.5V or less, the conventional circuit without this invention is incapable of keeping the logic level stable, thereby switching on the switching circuit 10 and allowing the recording driving current I_w to be supplied to the laser 3. With the improved circuit of this invention, on the other hand, when the source voltage of the control logic circuit 11 reaches 4.5V or less, the voltage monitoring circuit 23 serves to monitor a voltage drop and generate the voltage abnormality indicating signal f , thereby causing the transistor 21 to be conductive. The transistor 21 is served as a bypass for the recording driving current I_w . Since the current I_w bypasses the laser 3, the laser is unable to emit a laser beam having such high luminous intensity as being set in the recording mode. It results in preventing the recording film from being damaged by the laser 3.

Fig.5 is a circuit diagram showing the second embodiment of the present invention, in which the same components of this embodiment as the first one are referenced by the same reference notes. From this figure, it will be understood that a connecting portion of a bypass transistor 21 is different from that of the first embodiment. That is, the collector of the bypass transistor 21 is connected to the emitter of the transistor 9 included in the recording power producing circuit 13. From this connection, when the source voltage V_D of the control logic circuit 11 reaches a given voltage or less, therefore, the voltage monitoring circuit 23 serves to supply a high-level signal, thereby causing the transistor 21 to be conductive. Since the transistor 21 serves as a bypass of the recording power producing circuit 13, no excess current is allowed to flow through the laser 3.

Many widely different embodiments of the present invention may be constructed without departing from the spirit and scope of the present invention. It should be understood that the present invention is not limited to the specific embodiments described in the specification, except as defined in the appended claims.

There are described above novel features which the skilled man will appreciate give rise to advantages. These are each independent aspects of the invention to be covered by the present application, irrespective of whether or not they are included within the scope of the following claims.

Claims

1. A semiconductor laser driving circuit comprising:
 - a reproduction power producing circuit for producing a current to be supplied to a semiconductor laser for reproducing data recorded in an optical disk by applying a laser beam emitted from said laser to said disk;
 - a recording power producing circuit for producing a current to be supplied to said laser for recording data in said disk by applying a laser beam emitted from said laser to said disk;
 - a control logic circuit for controlling supply of said currents to said laser;
 - monitor means for monitoring a change of voltage of a power source connected to said control logic circuit; and
 - means for reducing a current being supplied to said laser to within a predetermined value when the change monitored by said monitor means exceeds a predetermined limit.
2. A driving circuit according to claim 1, further comprising a photodetector for detecting a luminous intensity of a laser beam emitted from said laser.
3. A driving circuit according to claim 2, wherein said reproduction power producing circuit includes a transistor connected to a power source through a resistor at an emitter thereof and to said laser at a collector thereof, a current-to-voltage converting circuit for converting a current generated by said photodetector into a voltage, an operational amplifier for amplifying said voltage, and a switching circuit connected to an output terminal of said amplifier and to a base of said transistor through a resistor, an output signal of said amplifier being supplied to said base when said switching circuit is closed, closing of said switching circuit being controlled by said control logic circuit.
4. A driving circuit according to claim 1, wherein said recording power producing circuit includes a recording power setting circuit, a transistor connected to a power source at an emitter thereof through a resistor and to said recording power setting circuit at a base thereof, and a switching circuit connected to a collector of said transistor and to said laser, said collector being connected to said laser when said switching circuit is closed closing of said switching circuit being controlled by said control logic circuit.
5. A driving circuit according to claim 1, wherein said monitor means includes a Zener diode, a comparator, and a first to third resistors, said Zener diode being connected at a cathode thereof to both said power source connected to said control logic circuit and a non inverting input terminal of said comparator through the first resistor and at an anode thereof to an inverting input terminal of said

comparator and the ground through the second resistor, said non-inverting input terminal being grounded through the third resistor.

6. A driving circuit according to claim 1, wherein said reducing means comprises a bypass transistor whose base is connected to an output terminal of said comparator through a resistor. 5

7. A driving circuit according to claim 6, wherein a collector of said bypass transistor is connected to an input terminal of said laser. 10

8. A driving circuit according to claim 6, wherein a collector of said bypass transistor is connected to the emitter of said transistor included in said recording power producing circuit.

9. A semiconductor laser driving circuit comprising a recording power producing circuit (13) for producing current to be supplied to a semiconductor laser (3) for recording data on an optical recording medium by applying a laser beam emitted from said laser to said medium; a control logic circuit (11) for controlling the supply of said current to said laser (3) in accordance with the data to be recorded; and means (21, 23) responsive to a supply voltage to the control logic circuit (11) falling to a predetermined level corresponding to the lowest level at which said control logic circuit is operable, to reduce the current supplied to the laser so as to inhibit damage to recorded data on the medium upon switching of the driving circuit. 15 20 25

10. A laser driving circuit in which current supply for the laser is forcibly reduced when the supply voltage to a logic control circuit which operates a laser current switch falls to a level below which the logic control circuit is inoperable and the switch might therefore otherwise pass laser current which could damage recorded data. 30 35

40

45

50

55

Fig. 1




Fig. 2




Fig. 3




Fig. 4





Fig. 5



(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11) Publication number:

0 405 952 A3

(12)

EUROPEAN PATENT APPLICATION

(21) Application number: 90307046.4

(51) Int. Cl.⁵: **G11B 7/125, H01S 3/10,
H01S 3/103**

(22) Date of filing: 27.06.90

(30) Priority: 28.06.89 JP 165577/89

(43) Date of publication of application:
02.01.91 Bulletin 91/01(84) Designated Contracting States:
DE FR GB IT NL(88) Date of deferred publication of the search report:
04.03.92 Bulletin 92/10(71) Applicant: **SHARP KABUSHIKI KAISHA**
22-22 Nagaike-cho Abeno-ku
Osaka 545(JP)

(72) Inventor: Numata, Tomiyuki, Akebono-Ryo

2613-1, Ichinomoto-cho

Tenri-shi, Nara-ken(JP)

Inventor: Kojima, Kunio

2-7-8-305 Shibatsuji-cho

Nara-shi, Nara-ken(JP)

Inventor: Deguchi, Toshihisa

C-722 Daiya-Haitsu-Gakuenmae, 2-200-5
Gakuen

Daiwa-cho, Nara-shi, Nara-ken(JP)


Inventor: Terashima, Shigeo

95-86 Kaminosho-cho

Nikaide, Tenri-shi, Nara-ken(JP)

(74) Representative: **Brown, Kenneth Richard et al**
R.G.C. Jenkins & Co. 26 Caxton Street
London SW1H 0RJ(GB)(54) **Semiconductor laser driving circuit.**

(57) The invention provides an improvement of the conventional laser driving circuit mainly including a control logic circuit (11), a reproducing power producing circuit (12), and a recording power producing circuit (13) for preventing a recording film of a disk from being damaged by a laser in a reproducing mode. The improved respect is addition of a voltage monitoring circuit (23) and a bypass transistor (21) for an abnormal signal. The voltage monitoring circuit monitors (23) a voltage drop caused in the control logic circuit and supplies a voltage abnormality indicating signal, thereby causing the bypass transistor (21) to be conductive for allowing the abnormal signal to be flown therethrough.

Fig. 3



European
Patent Office

EUROPEAN SEARCH REPORT

Application Number

EP 90 30 7046

DOCUMENTS CONSIDERED TO BE RELEVANT

Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.5)
X	PATENT ABSTRACTS OF JAPAN vol. 7, no. 228 (P-228)(1373) 8 October 1983 & JP-A-58 118 042 (HITACHI SEISAKUSHO K.K.) 13 July 1983 * abstract ** -- --	1,9,10	G 11 B 7/125 H 01 S 3/10 H 01 S 3/103
A	PATENT ABSTRACTS OF JAPAN vol. 8, no. 38 (P-255)(1475) 18 February 1984 & JP-A-58 189 849 (TOKYO SHIBAURA DENKI K.K.) 5 November 1983 * abstract ** -- --	1,2,9,10	
A	US-A-4 685 097 (VAN DER PUT) * the whole document ** -- --	1,2,9	
A	EP-A-0 256 827 (SONY CORPORATION) * the whole document ** -- --	1,2,9	
A	EP-A-0 219 124 (SHARP K.K.) * the whole document ** -- --	1,2,9	
A	EP-A-0 082 357 (MATSUSHITA ELECTRIC IND CO LTD) * the whole document ** -- -- -- --	1,2,9	TECHNICAL FIELDS SEARCHED (Int. Cl.5) G 11 B H 01 S
The present search report has been drawn up for all claims			
Place of search The Hague		Date of completion of search 11 December 91	Examiner BENFIELD A.D.
<div><div>CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention</div><div>E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</div></div>			